

- Compact & Lightweight chassis
- IEPE amplifier via BNC Input/Output connectors
- Individual channel gain selection x1, x10, x100
- Power on indication
- Signal level indicator per channel
- $\pm 10\text{VAC}$ output
- DC powered; Mains adaptor supplied



The 3X-I is a 3 channel IEPE signal conditioning unit, housed in a compact and rugged chassis. Featuring DC power input, it can be used via the supplied mains DC adaptor or via a field-based DC supply such as battery.

Each channel has independent gain control x1, x10, x100 and inputs and output connections are via front panel BNC connectors, making connection quick and simple. An earth/floating switch is mounted on the rear panel.

A signal level indicator is also provided for each channel via a multi coloured LED:

- Green – OK
- Red – Short circuit
- Off – Open circuit

Gain setting	Input	Output
X1	1mV	1mV
X10	1mV	10mV
X100	1mV	100mV

Specification		
Channels	3	
Power Input	9 – 30 Volts DC, 5 Watt. (nominal 18VDC)	
Power connection	2.1mm DC Socket	
Signal Connections	BNC Jacks - Input and Outputs on front panel	
Indicators - Power	External LED indicator shows correct power to unit	
Indicators - Signal	Multi coloured LED per channel, Green – OK/ Red – Short Circuit/ OFF – Open Circuit	
Floating or Ground	Selectable via rear panel switch	
IEPE power	24VDC, 4mA	
Signal level output	± 10 VAC pk-pk	
Dimensions	Height - 123mm, Width 45mm, Depth 196mm	
Weight	570grams	
Operating Temp.	0 to 45 °C, non-condensing.	
Broadband Electrical Noise	(1 to 10,000Hz) (Gain x1)	48.1 μVrms
	(1 to 10,000Hz) (Gain x10)	79.7 μVrms
	(1 to 10,000Hz) (Gain x100)	498 μVrms
Bandwidth	Gain x1	500kHz
Bandwidth	Gain x10	500kHz
Bandwidth	Gain x100	100kHz

Due to continued product development Kemo Limited reserve the right to change specification without notice.

Kemo Limited

First Floor, 33 King Street, Thetford, Norfolk, IP24 2AW, United Kingdom

+44 (0)1474 705168

www.kemo.com sales@Kemo.com